



SB100

Fingertip Pulse Oximeter

Fingertip SpO₂ incorporates the electronics and sensor into one unit that provides a cost-effective solution for spot-checks and short-term monitoring.

Fingertip SpO₂ is not influenced by the patient's movement; therefore, it gives patients the freedom of having their physical checkup anywhere and anytime they want. It can even be incorporated into an athletic activity.

SB100

Fingertip Pulse Oximeter

Features ▼

- Accurate Pulse Rate and Blood Saturation delivers in seconds.
- One-touch ON/OFF keypad for easy operation.
- Big, bright LED display for easy reading.
- Compact and light for mobility.
- Two AAA Alkaline batteries for easy power supply.
- Automatic Power-off after 10 seconds idling to save power.



Health at your Fingertip! Without lifting a finger

Specification

Scope of Measurement	SpO ₂ : 35% ~ 99%	Pulse rate: 30 ~250 bpm
Precision	SpO ₂ : 70% ~ 100% ± 2 digits(%)	35% ~ 69% : unspecified
Pulse rate	30 ~ 250±3 bpm	
Averaging	4 for SpO ₂ ; 8 for Pulse rate	
Weight	37g	
Size(HxWxD)	3.5 x 34 x 36 mm	
Power Supply	2 "AAA" alkaline (Can be used for 14 hours)	
Environmental Conditions	Operating Temperature: 41°F ~ 104°F (5°C ~ 40°C)	
	Storage Temperature : -4°F ~ 158°F (-20°C ~ 70°C)	
	Operating Humidity : 15% ~ 95%, noncondensing	

Distributed by

Apex Medical Corp.
No. 9, Min Sheng St., Tu-Cheng,
New Taipei City, 23679, Taiwan
T +886 2 2268 3100
F +886 2 2268 6525
marketing@apexmedicalcorp.com
www.apexmedicalcorp.com
Print-2015/04 / All rights reserved
Specifications may change without notice.